

Smart LED Lighting



Z-Wave® Dimmable LED Light Bulb

The Smart LED Bulb is a Z-Wave controllable and fully-dimmable, instant-on LED screw-in light bulb that provides pleasant soft-white illumination. Equivalent to a 60-watt incandescent bulb and using only nine (9) watts of energy. It is estimated to save approximately \$140 (USD) throughout its average lifespan*.

It offers users the convenience of wirelessly controlling lighting from a Z-Wave hub or controller, and lets users program scenes to create comfortable, inviting lighting settings to suit a variety of occasions and moods.

FEATURES

- Wirelessly control the bulb from anywhere (requires Z-Wave App for iOS or Android)
- Turn the bulb ON, OFF, or use its dimming features to adjust to 100 levels of brightness
- Acts as a wireless repeater to extend the Z-Wave mesh network to cover longer distances

SPECIFICATIONS

- Item Weight: 3.3 oz
- Product Dimensions (DxH): 2.5 x 4.4 in
- Shape: A19
- Z-Wave Chip: 500 series
- Wireless Range (Line of Sight): 130 ft
- Z-Wave Repeater: Yes
- Network Inclusion: Standard & NWI
- Power Consumption: Nine (9) Watts
- Max Output: 750 Lumens
- Equivalent Incandescent Output: 60 Watts
- Light Output: 2700 Kelvin
- *Average Lifespan (Based on usage of three (3) hours/day): ~25,000 Hours (~22.8 years)

SYSTEM REQUIREMENTS

- Go!Control® Panel security system or other Z-Wave-certified gateway
-